

EL-KP

Lighting System Keypad

Features

- ▶ Complies with BS5266
- ▶ Provides control over FIREscape system
- ▶ Easy-to-read LCD display
- ▶ Robust design
- ▶ Slim profile
- ▶ Password protected menus
- ▶ Programmable function buttons.



Description

EL-KP is an emergency lighting control panel keypad for use with the the Nepto-3K/HO and EL-2 lighting control panels. The control panel is operated and interrogated through the compact backlit LCD graphical display of the keypad, which can show system status of the lighting units including battery capacity.

One FIREscape control panel can support a total of 8 EL-KP keypads. One EL-KP can control up to 12 networked Nepto-3K/HO control panels.

Technical information

Nominal voltage	12 - 24 VDC
Materials	LCD graphical display 128 x 64 pixels
Display viewing area (mm)	60.0 x 32.5
Case colour	Light grey
Dimensions (mm)	147W x 144H x 29D
Material / Colour	Metal alloy, powder coated/Ivory
Weight (g)	410



For further information visit our website. Hochiki reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki to be a complete and up-to-date description. Check online for current version.

